



TOTAL INGENIEROS S.A.C
VENTAS, PROYECTOS, SERVICIOS EN INGENIERIA Y SISTEMAS DE REFRIGERACIÓN

Industrial Refrigeration Control Components



Dofun

Atlas For Selecting Models

山东东阀制冷科技有限公司
Shandong DoFun Refrigeration Technology Co., Ltd



山东东阀制冷科技有限公司

1、技术参数 Technical Parameter

- ◆ 公称通径: DN6-DN10
Nominal Diameter: DN6-DN10
- ◆ 公称压力: 4.0MPa、6.3MPa
Nominal Pressure: 4.0MPa, 6.3MPa
- ◆ 适用介质: R12, R22, R502, R134a, R404a, R507, R717, R744 等制冷剂。
Applicable Medium: R12, R22, R502, R134a, R404a, R507, R717, R744 and other refrigerants.
- ◆ 适用温度: -46°C ~ +150°C
Applicable Temperature: -46 °C ~ + 150 °C



2、订货 Order Goods

- ◆ 订货需指定型号、结构形式、公称压力
Please tell us the model, structural type and nominal pressure you want when ordering.
- ◆ 例: PGV10-A 表示DN10角式压力表阀, 公称压力4.0MPa
E.g: PGV10-A It means DN10 Angle Type Pressure Gauge Valve, Nominal Pressure is 4.0MPa.
PGV10-S 表示DN10直通压力表阀, 公称压力4.0MPa
PGV10-S It means DN10 Straight Type Pressure Gauge Valve, Nominal Pressure is 4.0MPa.
PGV10-HS 表示DN10直通压力表阀, 公称压力6.3MPa
PGV10-HS It means DN10 Straight Type Pressure Gauge Valve, Nominal Pressure is 6.3MPa.
压力表阀接压力表螺母默认M20×1.5, 左旋, 需要其它连接尺寸 时需指明
The nut of the Pressure Gauge Valve connected to the pressure gauge defaults to M20×1.5, left-handed, and it should be specified when other connection dimensions are required.



按照需要配置DN6、DN10接头, 角式配置可以根据需求加工不同的 中心尺寸, 图示为默认配置尺寸

According to the need to configure DN6, DN10 joints, angle configuration can be processed according to different center sizes, the diagram shows default configuration size.



螺纹连接系列压力表阀门螺纹规格表 Thread Specification Table Of Thread Connection Pressure Gauge Valve			
型号	进口尺寸	出口尺寸	备注
Model	Inlet Size	Outlet Size	Remark
PGV(S/A)-01	M20×1.5	M20×1.5	外螺纹
PGV(S/A)-02	NPT 1/4	NPT 1/4	
PGV(S/A)-03	NPT 3/8	NPT 3/8	进口外螺纹, 出口内螺纹
PGV(S/A)-04	NPT 1/2	NPT 1/2	
PGV(S/A)-05	MPT 1/4	FPT 1/4	进口外螺纹
PGV(S/A)-06	MPT 3/8	FPT 3/8	出口内螺纹 55°密封
PGV(S/A)-07	MPT 1/2	FPT 1/2	管螺纹

直通/角式配置可以根据需求加工不同的中心尺寸, 图示默认配置尺寸。

The straight/angle configuration can process different center sizes according to requirements, and the diagram is default configuration size.

